Low Pass Filter

LFCN-2000+

 50Ω

DC⁽¹⁾ to 2000 MHz

Maximum Ratings


| Operating Temperature | -55°C to 100°C |
|-----------------------|-----------------|
| Storage Temperature | -55°C to 100°C |
| RF Power Input* | 9W max. at 25°C |


^{*} Passband rating, derate linearly to 4W at 100°C ambient. Permanent damage may occur if any of these limits are exceeded

Pin Connections

| RF IN | 1_ |
|--------|-----|
| RF OUT | 3 |
| GROUND | 2,4 |

Outline Drawing






Suggested Layout, Tolerance to be within ±.002

Outline Dimensions (inch)

| | G .169 4.29 | .009 | .032 0.81 | .020 | C .037 0.94 | .063 | A .126 3.20 |
|-------|-------------------|------|--------------|------|-------------------|------|-------------------|
| wt | Р | N | M | L | K | J | Н |
| grams | .071 | .012 | .087 | .024 | .122 | .024 | .087 |
| .020 | 1.80 | 0.30 | 2.21 | 0.61 | 3.10 | 0.61 | 2.21 |

Demo Board MCL P/N: TB-270 Suggested PCB Layout (PL-137)



. COPLANAR WAYEGUIDE PARAMETERS ARE SHOWN FOR ROGERS RO4350B WITH THICKNESS .020" ± .0015". COPPER: 1/2 0Z. EACH SIDE. FOR OTHER MATERIALS TRACE WIDTH & GAP MAY NEED TO BE MODIFIED.

BOTTOM SIDE OF THE PCB IS CONTINUOUS GROUND PLANE.

DENOTES PCB COPPER LAYOUT WITH SMOBC
(SOLDER MASK OVER BARE COPPER)

DENOTES COPPER LAND PATTERN FREE OF SOLDER MASK

Features

- · excellent power handling, 9W
- small size
- 5 sections
- temperature stable
- LTCC construction

Applications

- harmonic rejection
- VHF/UHF transmitters/receivers
- lab use

CASE STYLE: FV1206

+RoHS Compliant The +Suffix identifies RoHS Compliance. See our web site for RoHS Compliance methodologies and qualifications



Electrical Specifications(1,2) at 25°C


| Pa | rameter | F# | Frequency (MHz) | Min. | Тур. | Max. | Unit |
|-----------|----------------|-------|-----------------|------|------|------|------|
| | Insertion Loss | DC-F1 | DC-2000 | _ | _ | 1.5 | dB |
| Pass Band | Freq. Cut-Off | F2 | 2275 | _ | 3.0 | _ | dB |
| | VSWR | DC-F1 | DC-2000 | _ | 1.3 | _ | :1 |
| Stop Band | Rejection Loss | F3 | 3000 | 20 | _ | _ | dB |
| | | F4-F5 | 3100-3500 | _ | 30 | _ | dB |
| | | F6 | 4600 | _ | 20 | _ | dB |
| | VSWR | F3-F6 | 3000-4650 | _ | 20 | _ | :1 |

(1) In Application where DC voltage is present at either input or output ports, coupling capacitors are required. Alternatively, if DC pass IN-OUT is required, Mini-Circuits' "D" suffix version of this model will support DC IN-OUT, and provide>100 MOhm isolation to ground.

(2) Measured on Mini-Circuits Characterization Test Board TB-270.

Typical Frequency Response ATTENUATION DC F1 F2 F3 F4 FREQUENCY


Electrical Schematic



Typical Performance Data at 25°C

| Frequency (MHz) | Insertion Loss (dB) | VSWR (:1) |
|--------------------|------------------------|----------------|
| | | |
| 10.00 | 0.14 | 1.04 |
| 258.75 | 0.30 | 1.19 |
| 507.50 | 0.35 | 1.23 |
| 756.25 | 0.51 | 1.28 |
| 1005.00 | 0.49 | 1.21 |
| 1253.75 | 0.56 | 1.18 |
| 1502.50 | 0.60 | 1.14 |
| 1751.25 | 0.74 | 1.13 |
| 2250.00 | 4.73 | 5.33 |
| 2500.00 | 11.34 | 16.41 |
| 2750.00 | 19.65 | 43.44 |
| 3000.00 | 32.99 | 102.19 |
| 4244.00 | 20.09 | 217.15 |
| | | |
| 4600.00 | 20.32 | 46.96 |
| 4422.00 4600.00 | 19.52 20.32 | 66.82 46.96 |





Notes
A. Performance and quality attributes and conditions not expressly stated in this specification document are intended to be excluded and do not form a part of this specification document.
B. Electrical specifications and performance data contained in this specification document are based on Mini-Circuit's applicable established test performance criteria and measurement instructions.
C. The parts covered by this specification document are subject to Mini-Circuits standard limited warranty and terms and conditions (collectively, "Standard Terms"); Purchasers of this part are entitled to the rights and benefits contained therein. For a full statement of the Standard Terms and the exclusive rights and remedies thereunder, please visit Mini-Circuits' website at www.minicircuits.com/MCLStore/terms.jsp