Technical Data

Metal Switches




Series D


Description D-SU2 VKS 90GR

Article number 6142200765


Operating symbol




Operating diagram



Self arresting off 33°







Tolerances

Operating point: ± 3,5°; Operating torque: ± 10%

Electrical data		
Rated insulation voltage	Ui	400 V AC
Conv. thermal current	I_{the}	10 A
Rated operational voltage	U_e	240 V
Utilization category		AC-15, U _e /I _e 240 V/3 A
Short-circuit protective device		Fuse 2 A gL/gG
Protection class		I

This document will not become the contractual basis; the details included herein do not constitute any descriptions of expected conditions, so that warranties/claims for defects on account of possible variations of the actual qualities from the qualities described herein are explicitly excluded. All rights reserved. Specifications subject to change without notice!

Technical Data





Mechanical data	
Enclosure	Die-cast aluminium
Cover	Sheet aluminium
Actuator	Lever (St)
Ambient air temperature	-40 °C/ +80 °C
Contact type	2 NO, 2 NC
Mechanical life	1 x 10 ⁶ operating cycles
Switching frequency	≤ 50 / min.
Assembly	4 x M5
Connection	8 screw terminals (M3,5)
Conductor cross-sections	Solid: 0,5 1,5mm ²
	Litz wire with ferrules: 0,5 1,5mm ²
Cable entrance	2 x M20 x 1,5
Weight	≈ 0,4 kg
Installation position	Operator definable
Protection type	IP65 acc. to IEC/EN 60529

Actuation

The actuating device is preferably started from 2 sides.

By loosening the 4 screws the actuation assembly can be rotated in 90 degree increments such that 4 actuation directions are possible.

The actuation assembly is to be again fastened to the housing using the 4 screws.

Standards	VDE 0660 T100, DIN EN 60947-1, IEC 60947-1
	VDE 0660 T200, DIN EN 60947-5-1, IEC 60947-5-1
EU Conformity	C€
Approvale	CSA A300 (cama polarity)
Approvals	_C CSA _{US} A300 (same polarity)

Notes

The degree of protection specified (IP code) applies only to a properly closed cover and the use of an equivalent cable gland with adequate cable. The switch has to be protected from all kinds of weather conditions.